
## LTspice IV



- Free Analog Circuit Simulator
- Unlimited Nodes/Nets
- Fast Simulations

LTspice® is a high performance SPICE simulator, schematic capture and waveform viewer designed to speed the process of power supply design. LTspice adds enhancements and models to SPICE, significantly reducing simulation time compared to typical SPICE simulators, allowing one to view waveforms for most switching regulators in minutes compared to hours for other SPICE simulators.



Follow @ LTspice on Twitter for up-to-date information on models, demo circuits, events and user tips



## www.linear.com/ltspice

Included in the download is a complete and fully functional SPICE program, help files, macro models for Linear Technology's power products, over 200 op amp models, as well as models for resistors, transistors and MOSFETs.



Sign up for the Linear Insider email newsletter to receive LTspice updates @ www.linear.com/mylinear





	LTspice HotKeys					
LT	Schematic	Symbol	Waveform	Netlist		
Modes	ESC - Exit Mode	ESC - Exit Mode				
	F3 – Draw Wire					
	F5 – Delete	F5 – Delete	F5 – Delete			
	F6 – Duplicate	F6 – Duplicate				
	F7 – Move	F7 – Move				
	F8 – Drag	F8 – Drag				
	F9 – Undo	F9 – Undo	F9 – Undo	F9 – Undo		
	Shift+F9 – Redo	Shift+F9 – Redo	Shift+F9 – Redo	Shift+F9 – Redo		
	Ctrl+Z – Zoom Area	Ctrl+Z – Zoom Area	Ctrl+Z – Zoom Area			
	Ctrl+B – Zoom Back	Ctrl+B – Zoom Back	Ctrl+B – Zoom Back			
	Space – Zoom Fit		Ctrl+E – Zoom Extents			
e w	Ctrl+G – Toggle Grid		Ctrl+G – Toggle Grid	Ctrl+G – Goto Line #		
Vie	U – Mark Unncon. Pins	Ctrl+W – Attribute Window				
>	A – Mark Text Anchors	Ctrl+A – Attribute Editor	Ctrl+A – Add Trace			
	Atl+Click - Power		Ctrl+Y – Vertical Autorange	Ctrl+R – Run Simulation		
	Ctrl+Click - Attr. Edit		Ctrl+Click - Average			
	Ctrl+H – Halt Simulation		Ctrl+H – Halt Simulation	Ctrl+H – Halt Simulation		
	R – Resistor	R – Rectangle	Command	Line Switches		
	C – Capacitor	C – Circle	Flag Short Descrip			
	L – Inductor	L – Line				

Command Line Switches				
Flag	Short Description			
-ascii	Use ASCII .raw files. (Degrades performance!)			
-b	Run in batch mode.			
-big or -max	Start as a maximized window.			
-encrypt	Encrypt a model library.			
-FastAccess	Convert a binary .raw file to Fast Access Format.			
-netlist	Convert a schematic to a netlist.			
-nowine	Prevent use of WINE(Linux) workarounds.			
-PCBnetlist	Convert a schematic to a PCB netlist.			
-registry	Store user preferences in the registry.			
-Run	Start simulating the schematic on open.			
-S0I	Allow MOSFET's to have up to 7 nodes in subcircuit.			
-uninstall	Executes one step of the uninstallation process.			
-wine	Force use of WINE(Linux) workarounds.			

## LTspice IV

D – Diode G – GND

T – Text

S – Spice Directive

F2 – Component F4 – Label Net Ctrl+E – Mirror

Ctrl+R - Rotate



See Demo

A – Arc

T - Text

Ctrl+E - Mirror

Ctrl+R - Rotate

Oulillialla	Ollott Description			
.AC	Perform a Small Signal AC Analysis			
.BACKANNO	Annotate the Subcircuit Pin Names on Port currents			
.DC	Perform a DC Source Sweep Analysis			
.END	End of Netlist			
.ENDS	End of Subcircuit Definition			
.FOUR	Compute a Fourier Component			
.FUNC	User Defined Functions			
.FERRET	Download a File Given the URL			
.GLOBAL	Declare Global Nodes			
.IC	Set Initial Conditions			
.INCLUDE	Include another File			
.LIB	Include a Library			
.LOADBIAS	Load a Previously Solved DC Solution			
.MEASURE	Evaluate User-Defined Electrical Quantities			
.MODEL	Define a SPICE Model			
.NET	Compute Network Parameters in a .AC Analysis			
.NODESET	Supply Hints for Initial DC Solution			
.NOISE	Perform a Noise Analysis			
.0P	Find the DC Operating Point			
.OPTIONS	Set Simulator Options			
.PARAM	User-Defined Parameters			
.SAVE	Limit the Quantity of Saved Data			
.SAVEBIAS	Save Operating Point to Disk			
.STEP	Parameter Sweeps			
.SUBCKT	Define a Subcircuit			
.TEMP	Temperature Sweeps			
.TF	Find the DC Small-Signal Transfer Function			
.TRAN	Do a Nonlinear Transient Analysis			
.WAVE	Write Selected Nodes to a .WAV file			
Cuttiv Cuttiv Constants				
Suffix Constants				

**Simulator Directives - Dot Commands** 

**Short Description** 

Command

Suffix		Suffix	
		f	1e-15
T	1e12	р	1e-12
G	1e9	n	1e-9
Meg	1e6	u	1e-6
K	1e3	M	1e-3
		Mil	25.4e-6

Constants				
E	2.7182818284590452354			
Pi	3.14159265358979323846			
K	1.3806503e-23			
Q	1.602176462e-19			
TRUE	1			
FALSE	0			

